# VAISALA

## Vaisala Telemetry Antenna RB31



The Vaisala Telemetry Antenna RB31 has no moving parts and is controlled automatically by a Vaisala telemetry receiver. The RB31 is delivered as a complete unit and is easy to install. The RB31 is protected by a radome against rain and high winds, and has six monopoles with corner reflectors and a cross dipole. The dipole

and mono-poles are connected by means of a diode switch. The Vaisala telemetry receiver controls the switch, selecting the best available element for signal reception. A lownoise amplifier unit compensates for cable losses.

The standard RB31 includes a mounting pedestal and flange for roof

installation. Optionally, the RB31 can be mounted on a pole mast with a special mast mounting.

### **Technical data**

#### **Antenna**

Frequency range	400 406 MHz
Horizontal directivity	8 dBi
Vertical directivity	-3 dBi
Polarization near horizon	Vertical
Polarization at zenith	Circular
Number of corner reflectors	6

**Amplifier** 

Gain	20 dB typical
Noise figure	<2 dB
Power input	+10 12 VDC,
	130 mA through RF cable
Output impedance	50 ohms,VSWR <1.5

### **Telemetry range**

Telemetry range with RS92-SGP radiosonde

Up to 350 km under normal sounding conditions

#### Mechanics

Connector	Coaxial 7/16
Maximum diameter	1.1 m
Height without pedestal	0.8 m
Height with pedestal	1.55 m
Weight	32 kg
Standard cable length	33 m (greater lengths possible
	with low-loss cable)

#### **Environmental conditions**

Operating temperature range	-4055 °C
Operating humidity range	0 100 %RH
Operating precipitation	Unlimited
Maximum wind speed	65 m/s
Storage temperature	-50 +100 °C
Storage humidity	0 100 %RH

